

# 4 Way Splitter 'F' Type 5-2400MHz

## Power Pass All Ports

### 17MM-DM04Q

#### Features and Benefits

- » Foxtel Approved (F30939)
- » Suitable for both Satellite/TDT & FTA
- » DC power pass all ports
- » 10dB extra screening with soldered back
- » Frequency range 5-2400 MHz
- » Also available in 50 pack (17MM-DM04QB)



#### Splitters and Taps

Matchmaster has a premium range of RF Splitters & Taps ranging from 1 Way through to 8 Way. We cater for both Terrestrial and Satellite frequencies with both Single Port AC/DC and All Port DC Power Pass products available.



#### 17MM-DM04Q Specifications

	Frequency	
Insertion Loss	5-40MHz	8.5dB
	40-470MHz	8.0dB
	470-1000MHz	8.0dB
	1000-1750MHz	8.0 to 9.0dB
	1750-2150MHz	9.0 to 10.0dB
	2150-2400MHz	10.0 to 11.5dB
Return Loss	5-40MHz	≥10dB
	40-470MHz	≥10dB
	470-1000MHz	≥10dB
	1000-1750MHz	≥10dB
	1750-2150MHz	≥10dB
	2150-2400MHz	≥10dB
Isolation	5-40MHz	≥20dB
	40-1000MHz	≥23dB
	1000-1750MHz	≥23dB
	1750-2400MHz	≥23dB
DC Power Passing	from all output to input	Max. 500mA